



# 2.4G LED Dimming Controller

## Main Characteristics

## RF Dimming Remote Control

Remote Option: Dimmina

Working Voltage: 3Vdc (Battery CR2032) 2 4GHz

Wireless Frequency: Working Temperature: -30°C~55°C

L150×W46×H18(mm) Package Size:

Weight(G.W.):

#### R4-3A CV Receiver

5~24Vdc Input Voltage:

3A × 4CH Max. 12A Max Current Load:

Max Output Power: 60W/144W/288W(5V/12V/24V)

Working Temperature: -30°C~55°C Package Size: L127×W35×H24(mm)

Weight(G.W.): 60a

#### R4-5A CV Receiver

Input Voltage: 5~24Vdc

5A × 4CH Max. 20A Max Current Load:

Max Output Power: 100W/240W/480W(5V/12V/24V)

Working Temperature: -30°C~55°C

L178×W48×H33(mm) Package Size:


Weight(G.W.): 150a


Note: Receiver is sold separately.














#### R4-CC CC Receiver

Input Voltage: 12~48Vdc Output Voltage: 3~46Vdc


CC 350/700/1050mA×4CH Output Current: 1.05W~48.3W×4CH Max 193.2W Output Power:


-30°C~55°C Working Temperature:


Package Size: I 178×W48×H33(mm)

Weight(G.W.): 165a

## **Dimensions**












## Operating Instruction for Remote:



#### Match/Clear code between remotes

## Match code:



#### Clear code:



Press the bottom two keys of B simultaneously (about 6 seconds), the indicator light keeps on, deactivated matching successfully.

#### Match/Clear code between remote and receiver

#### Match code:




# Operating Instruction for Receiver:







#### Clear code:



# Wiring Diagram:







#### Attention:

- · Please replace the battery if the remote becomes insensitive or control distance is shortened.
- · Please take out the battery for long time unused.

www.ltech-led.com Update time: 2016- 09- 29